

MAXX 3000 BATTERY TESTER



Basic Specification

Capacity range	No limit
Voltage range	Min0.00-Max220V(DC) Recommend 180V max
Resistance range	0.00m Ω ~ 20 Ω Accuracy: $\pm 1.0\% + 6$ digit
Temperature	0 $^{\circ}$ C ~ 50 $^{\circ}$ C
Humidity	<90%HR
Storage space	32K
LCD display	24 Characters
Power supply	10 pcs rechargeable AA batteries (1.2V 1800mAh each unit)
Connection port	USB port

WING MAXX 3000 BATTERY TESTER

A smart instrument used during battery maintenance which is designed to assess the condition of a wide range of lead acid batteries. It simultaneously tests battery voltage and internal resistance, thus giving an indication of relative capacity and battery condition. Enjoy efficient work with Maxx 3000 partner.

- Hand held device
- User friendly
- Single battery test
- Strings of batteries test
- Battery location and string information can be identified for easy comparison
- Test & Storage time within 2 seconds
- Test data on up to 2000 batteries can be stored
- User defined parameters can be downloaded from computer or set up directly in the tester
- Specialized clamp type probes suitable for different shapes of terminals
- Direct U-disk Media between tester and computer analysis system for test data management
- Buzzer alarm function
- Bright back lights for easy use
- Password management in key parts
- Excellent after service